



Color :  White, Ivory, Light Almond

UPC Code : 078477728512

Country Of Origin : China

DD0SR-DLZ

Decora Smart Switch Companion with Locator LED for Multi-Location Switching, 120/277VAC, 60Hz

The Decora Switch Companion is designed for use in a multi-location application only and must be used with a Leviton Decora Smart or Decora Digital switch, dimmer or fan speed control allowing the lighting or fan to be controlled from more than one location. The LED locator light makes it easy to spot in the dark and its stylish look is compatible with Leviton's other Decora devices and wallplates (sold separately). White face assembled on device with ivory and light almond face plates included. Change the color of the switch at any time by ordering a new face plate color change kit (DDKIT-S). Face plate colors include white, ivory, light almond, gray, black and brown.

- PRACTICAL – Turn lights or fan on/off from multiple locations
- VERSATILE – Can use in 3-way or up to 4 additional locations when used with Decora Smart (Z-Wave, Wi-Fi, Zigbee, HomeKit) OR Decora Digital switches, dimmers, or fan speed controls.
- INTUITIVE – Locator LED illuminates when load is off making it easy to locate in the dark
- ROBUST – Dual voltage 120/277 VAC. Neutral wire required for installation
- CONVENIENCE - Change the switch faceplate color to black, gray, brown, light almond, ivory or white using DDKIT-S

[Have Questions? Search the knowledge base.](#)

Technical Information

Product Features

Action : Rocker Switch for ON /OFF

Available Colors : White-W, Ivory-I, Light Almond-T, Gray-G, Black-E, Brown-B

Color : White, Ivory, Light Almond

Color Change Kit : DDKIT-S

Feature : 3-Way or Up to 4 Location Applications

Grounding : Grounding

LED Color : Green

Light : LED Locator

Pole : 3

Standards and Certifications
: CSA, NOM, FCC

Style Name : Decora
Termination : Side
Torque Range : 14 – 18 in.-lbs
Type : Companion Device
Voltage : 120/277 VAC
Wallplate : Order Separately
Warranty : 5-Year Limited
Wiring Notes : Neutral required

Features and Benefits

- The Decora Switch Companion **must** be used with a primary Decora Smart (Wi-Fi, Z-Wave, HomeKit or Zigbee) or Decora Digital switch, dimmer or fan speed control
- Dual voltage for 120VAC and 277VAC applications
- For use in 3-way or up to 4 additional locations
- Locator LED illuminates when load is off making it easy to locate in the dark
- Intuitive operation and digital circuitry provide convenient and easy on/off operation
- Neutral wire required for installation. Neutral wires are typically two or more white wires in an electrical box. If you are unsure, consult an electrician
- White face assembled on device, Ivory and Light Almond faces included
- Change the switch faceplate color to black, gray, brown, light almond, ivory or white using DDKIT-S

Patents ^{*}

US8944859

This list is provided for patent marking purposes only. A good faith effort is made to maintain the accuracy and completeness of this list. No legal inference should be drawn from the omission of a patent from this list.

Leviton Manufacturing Co., Inc

201 North Service Road, Melville, NY 11747

Telephone: +1-800-323-8920 · FAX: +1-800-832-9538 · Tech Line (8:30AM-7:30PM E.S.
T. Monday-Friday): +1-800-824-3005

Leviton Manufacturing of Canada, Ltd.

165 Hymus Boulevard, Pointe Claire, Quebec H9R 1E9 · Telephone: +1-800-461-2002 ·
FAX: +1-800-824-3005 ·

Leviton S. de R.L. de C.V.

Lago Tana 43, Mexico DF, Mexico CP 11290 · Tel.: (+52)55-5082-1040 · FAX: (+52)
5386- 1797 ·

Visit our Website at: www.leviton.com

© 2025 Leviton Manufacturing Co., Inc. All Rights Reserved. Subject to change without notice.

Leviton has a global presence.

If you would like to know where your local Leviton office is located please go to:
www.leviton.com/company/about-leviton/locations

© 2025 Leviton Manufacturing Co., Inc.